

Сечение провода, мм <sup>2</sup> *	Диаметр под винт	Размер, мм					Упаковка, шт.	Код	
		C2	C1	L	A	B			D
70	6	12	16,5	40,5	21	24	6,4	25	2I6
	8			42,5		24	8,4	25	2I8
	10			43,5		24	10,5	25	2I10
	12			45		24	13	25	2I12
	14			46		25	15	25	2I14
	16			48,5		28	17	25	2I16
	20			52		29	21	25	2I21
95	6	13,5	18	43	23	26	6,4	25	2L6
	8			46		26	8,4	25	2L8
	10			47		26	10,5	25	2L10
	12			48		26	13	25	2L12
	14			51,5		26	15	25	2L14
	16			51		28	17	25	2L16
	20			55		30	21	25	2L21
120	8	15	20	49,5	26	29	8,4	25	2M8
	10			52		29	10,5	25	2M10
	12			51,5		29	13	25	2M12
	14			53		30	15	25	2M14
	16			55		30	17	25	2M16
	20			60		35	21	25	2M21
150	8	16,8	21,3	55,5	29	31	8,4	25	2N8
	10			56,5		31	10,5	25	2N10
	12			56		31	13	25	2N12
	14			57		31	15	25	2N14
	16			58		31	17	25	2N16
	20			63		35	21	25	2N21
	185			8		19	24	58	30
10		59	35	10,5	25			2O10	
12		58,5	35	13	25			2O12	
14		61	35	15	25			2O14	
16		63	35	17	25			2O16	
20		66	35	21	25			2O21	
240		8	21	26	67			35	
	10	67			38	10,5	25		2P10
	12	67			38	13	25		2P12
	14	69			38	15	25		2P14
	16	69,5			38	17	25		2P16
	20	71			38	21	25		2P21
300	10	24	30	79,5	42	44	10,5	20	2Q10
	12			82		44	13	20	2Q12
	14			84		44	15	20	2Q14
	16			85		44	17	20	2Q16
	20			85		44	21	20	2Q21
400	10	27,5	33,5	92	47	49	10,5	15	2R10
	12			92		49	13	15	2R12
	16			92		49	17	15	2R16
	20			92		49	21	15	2R21
500	12	31	38	113	70	55,5	13	5	2S12
	16			113		55,5	17	5	2S16
	20			113		55,5	21	5	2S21
630	16	34	41	115	70	60	17	5	2T16
	20			115		60	21	5	2T21

\* Сечение провода для 1–3 класса гибкости